

DOREMI SERVERS AT ACCESS IT SITES
IMPORTANT INFORMATION FOR BOLT 3-D!!!

If you are using a Doremi Server and your site is part of the Access IT rollout, you must follow the instructions below. Failure to follow these instructions will result in the improper playback of the content provided. To determine your TCC software version, please check the bottom right of the main TCC screen with the AccessIT logo.

Building Playlists for 3-D Presentation on a AIX DCP-2000 with 2.4 TCC:

1. Start → Show Editor
2. Click on the New Button to add a New playlist. Name it "**BOLT 3D**"
Click OK.
3. Add all the content in the Disney Show Playlist and the optional content if required in this order:
 - 3D-Black-10sec_POL_F_51_2K_20081016_TDC_i3D
 - 3D-Black-5sec_POL-1_F_51_2K_20080118_TDC_i3D
 - 2D Trailer Content
 - 3D-Black-5sec_POL-1_F_51_2K_20080118_TDC_i3D
 - Put on Your 3D Glasses Card
 - Recycle your 3D glasses (**Real D 3D Systems Only**)
 - 3D Trailers
 - Disney 3D digital logo
 - Bolt 3D feature
 - Rating Card
 - 3D-Black-5sec_POL-1_F_51_2K_20080118_TDC_i3DPlease see attached image for reference
4. Go to the Cue Tab
5. Drag the **Close Dowser** cue to the first 10 second black. Select the **BC** option and type in 00:00:01
6. Drag the **Start_Flat** cue to the first 10 second black. Select the **BC** option and type in 00:00:01
7. Drag the **48 FPS Mode** cue to the first 10 second black. Select the **BC** option and type in 00:00:05
8. Drag the **3D_FLAT_1998** cue to the first 10 second black. Select the **BC** option and type in 00:00:10

9. Drag the **Open Dowser** cue to the first 10 second black. Select the **BC** option and type in 00:00:10
10. Drag the **Close Dowser** cue to the second 5 second black. Select the **BC** option and type in 00:00:00
11. Drag the **48 FPS Mode** cue to the second 5 second black. Select the **BC** option and type in 00:00:00
12. Drag the **3D_FLAT_1998** cue to the second 5 second black. Select the **BC** option and type in 00:00:03
13. Drag the **Open Dowser** cue to the second 5 second black. Select the **BC** option and type in 00:00:05
14. Drag the **Feature** cue to the feature. Select the **BC** option and type in 00:00:01
15. Drag the **Close Dowser** cue to the last 5 second black. Select the **BC** option and type in 00:00:00
16. Other auditorium automation cues, such as lights up or masking adjustments may also be added as needed.
17. If you have any questions or problems you can't solve in 15min, please call your integrator or Technicolor at 1(800) 99- FILMS (option 2)

