

DOREMI SERVERS AT NON-ACCESS IT SITES
IMPORTANT INFORMATION FOR JONAS BROTHERS 3D!!!

If you are using a Doremi Server and your site is not part of the Access IT rollout, you must follow the instructions below. Failure to follow these instructions will result in the improper playback of the content provided.

Building Playlists and Macros for 3-D Presentation on a NON AIX DCP-2000:

1. Open the Macro Editor
Under Menu → Doremi Labs Folder → Select Macro Editor
2. Click on the + sign to add a New Macro. Name it "**48FPS_Mode**".
Click OK.
3. Click on Insert a New Action.
4. Click on Video Output Action, choose Play all clips at 48fps, then click Save.
5. Click on the + sign to add a New Macro. Name it "**24FPS_Mode**".
6. Insert New Action. Select Video Output Action. Choose the Video Default Action.
7. Click Save.
8. The Password Authentication Prompt will appear. Enter your password.
Click OK. Then select quit in the upper right corner.
9. Go to the menu and select CineLister Editor.
10. Click on the refresh button which is the green arrow button in the upper left corner. The green arrow is pointing down.
11. Attach the **Black_Automation_Cue_Clip_5sec** found on the supplied drive.
Once the clip is loaded it can be found under "transitional" in the selectable Elements window.
12. In the Element window highlight the **48FPS MODE** Macro. Click add to Show Playlist. The Edit Time window will appear. Select "From the beginning of the Clip". Push the return button.
13. In the Play Window, you will see the Black Automation Cue and underneath it you will see the **48FPS_Mode** Macro.

Continued on second page.

14. Add all the content in the Disney Show Playlist and the optional content if required.

15. Under automation cues select the **24FPS_Mode** macro. Place it at the end of the show playlist. The Edit Time Code window will appear. Within the Edit Time Code window select "From the end of the Clip". Push the return button.

16. Save the current Show Playlist.

Other auditorium automation cues, such as lights up or masking adjustments may also be added as needed.

If you have any questions or problems you can't solve in 15min, please call your integrator or Technicolor at 1(800) 99-FILMS (option 2).

THANK YOU!